

SLC DALI DT6 DIMMER MCU/SLAVE



52mA DALI dimmer. Built-in surge and overload protection. Can work both as master and slave. Modes: Group, Address, or Broadcast.

Technical data	
Product ID	S52000
DALI bus output power	52 mA
DALI-bus power consumption	4 mA
Protection class	II
Housing	Plastic housing
Programmable	Yes
Degree of protection (IP)	IP20
Number of colour channels	1
Operating method	DALI
Dimming interface	DALI DT6
Input	
Electrical connection (Input)	L`N screw connection
Input voltage	220.0 - 240.0 V
Output	
Max. output current	0.052 A
Output voltage	9.9 - 22.0 V
Installation	
Length	86 mm
Height	29 mm
Width	86 mm
Model	Static
Built-in	Yes
Surface-mounted	No
Suitable for outdoor use	No
DIN rail mounting	No
logistics data	
Brand	SLC
Imported by	The Light Group



17.04.2024

Subject to changes and printing errors