SLC LED-DRIVER CC 180MA 6,5W 20-38VDC DALI

Constant Current DALI driver for OneSoft & One360 Downlights. Preset to 180mA output current.



Technical data	
Product ID	SLC1136
DALI version	DALI2
DALI Type	DT6
Number of DALI-address	1
CE	Yes
Exterior color	White
EMC	Yes
ENEC	Yes
Flicker free	Yes
Operating temperature	-20°C ~ +45°C °C
Expected lifetime (Ta 45°C)	50000 Hours
Over temperature protection	Yes
Over voltage protection	Yes
RoHs	Yes
SELV	Yes
Short circuit protection	Yes
Tc	80 °C
Protection class	II
Housing	Plastic housing
Degree of protection (IP)	IP20
Suitable for constant current	Yes
Dimming DALI	Yes
Dimming method	Pulse Width Modulation (PWM)
Dimming interface	DALI DT6
Input	
Power factor	0.9
Input voltage	[100.0, 240.0] V
Frequency range	[50.0, 60.0] Hz
Inrush Current	0.25 A
Output	
Output power	5.5 - 10.5 W
Max total output power	10.5 W

29.03.2024

Subject to changes and printing errors

The Light Group AS, Sagmyra 2A, 4624 Kristiansand S, Norway
Tel.: +47 38 00 21 01 | E-Mail : post@tlg.no **www.tlg.no**

Output voltage	20.0 - 38.0 V
Max output current	0.35 A
Output current	150.0 - 350.0 mA
Mono	Yes
Installation	
Length	105.5 mm
Height	29.73 mm
Width	59.06 mm
Model	Static

The Light Group AS, Sagmyra 2A, 4624 Kristiansand S, Norway
Tel.: +47 38 00 21 01 | E-Mail : post@tlg.no **www.tlg.no**