



SLC DALI DT8 TW/CCT DIMMER MCU /SLAVE

100mA DALI DT8 dimmer for CCT/TW DALI Luminaries. Built-in surge and overload protection. Can work both as master and slave. Modes: Group, Address, or Broadcast.

Technical data	
Product ID	S52035
DALI Type	DT8
DALI bus output power	100 mA
DALI-bus power consumption	4 mA
Expected lifetime (Ta 25°C)	110000 Hours
Expected lifetime (Ta 45°C)	50000 Hours
Protection class	II
Housing	Plastic housing
Programmable	Yes
Degree of protection (IP)	IP20
Number of colour channels	2
Operating method	DALI
Dimming interface	DALI DT6
Input	
Electrical connection (Input)	L`N screw connection
Input voltage	220 - 240 V
Output	
Tunable White	Yes
Max. output current	0.1 A
Installation	
Length	83.8 mm
Height	83.8 mm
Width	52.4 mm
Model	Static
Built-in	Yes
Surface-mounted	No
Suitable for outdoor use	No
DIN rail mounting	No
logistics data	
Brand	SLC
Imported by	The Light Group

